



FEATURES



FUEL GAUGE

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



AVR

AVR is a device often solid state, for controlling the output



CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



LED DISPLAY

LED screen to monitor voltage and current with hourmeter



CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.



DUAL ELEMENT AIR FILTER



LARGE CAPACITY FUEL TANK

15-25lt

(Runtime may vary depending on fuel tank capacity)

GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	2,5
Maximum Power (kW)	2,8
AC Rated Corrent (A)	11
Voltage (V)	230
Frequency (Hz)	50
Phase Number	1
Power Factor	1
Fuel Consumption %100 (lt/h)	1,55
Fuel Consumption %75 (lt/h)	1,12
Fuel Consumption %50 (lt/h)	0,92
Noise Level (dB(A))	76
Sound Level (LwA)	96
Pole Number	2
Output Receptacle	2x16A/250v

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)



444 4 630

| www.aksa.com.tr



ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	5,8
Engine Output (kW)	4,3
Bore and Stroke	70x54
Compression Ratio	8,5
Cylinder Number	1
Displacement (ml)	208
Fuel Type	Gasoline
Oil Capacity (L.)	0,6
Fuel Tank Capacity (L.)	15
Starting System	Electric/Manual
Cooling System	Air Cooled
Battery Capacity	6.5Ah

DIMENSIONS AND WEIGHT

Width (mm.)	495
Lenght (mm.)	610
Height (mm.)	485
Dry Weight (kg.)	46,5