



Over Product

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Kracht (kVA)

3 Fasen, 60 Hz, PF 0.8

Spanning	Stand-by vermogen (ESP)		Prime Power (PRP)		Standby Amper
	kW	kVA	kW	kVA	
380/220	128,80	161,00	116,80	146,00	244,62
208/120	135,20	169,00	123,20	154,00	469,11
480/277	135,20	169,00	123,20	154,00	469,11

Stand-by vermogen (ESP) Het wordt gebruikt om te voldoen aan de variabele elektrische belastingvereiste in geval van uitval van de betrouwbare netvoeding. ESP voldoet aan ISO 8528-1 Overbelasting is niet toegestaan.

Prime Power (PRP) Wordt gedefinieerd als het continue bedrijfsvermogen onder variabele belasting. PRP voldoet aan ISO 8528-1 10% overbelasting kan elke 12 uur worden gedaan.

Algemene kenmerken

Modelnaam	AC 169-6
Frequentie (HZ)	60
Brandstoftype	Diesel
Motormerk en -model	CUMMINS 6BTAA 5,9-G6 - 60Hz
Alternatormerk en -model	UCI 274 E - 60Hz
Configuratiescherm Model	DSE 6020
Cabine	MS 60

MOTORSPECIFICATIES

Motor	CUMMINS
Motor model	6BTAA 5,9-G6 - 60Hz
Silindir Sayısı (L)	6 cylinders - in line
Bore (mm.)	102
Stroke (mm.)	120
Silindir Hacmi (lt.)	5.9
Aspiratie	Turbo Charged and AfterCooled
Compressieverhouding	16.5:1
Hız (d/dk)	1800
Olie capaciteit (Filtre Dahil) (lt)	16.4
Stand-by vermogen (kW/HP)	160/215
Blokverwarmingshoeveelheid	1
Blokkeer verwarmingsvermogen (Watt)	1000
Brandstoftype	Diesel
Injectietype en systeem	Direct





Type brandstofpomp	Bosch Rotary Type
Governor-systeem	Electronic
Bedrijfsspanning (Vdc)	12 Vdc
Batterij en capaciteit (aantal / Ah)	1x85
Laaddynamo (A)	55
Koelmethode	Water Cooled
Koelventilatorluchtstroom (m³ / min)	162
Koelvloeistofcapaciteit (alleen motor / met radiator) (lt)	9.1/21.4
Luchtfilter	Dry Type
Brandstofverbruik bij eerste 100% belasting (lt / uur)	39
Brandstofverbruik primair 75% belasting (lt / uur)	31
Brandstofverbruik bij eerste 50% belasting (lt / uur)	21

Dynamo specificaties

Fabrikant	Stamford
Alternatormerk en -model	UCI 274 E - 60Hz
Frequentie (HZ)	60
Kracht (kVA)	146
Spanning (V)	380
Fase	3
Automatische spanningsregelaar	AS440
Voltage regulatie	(+/-)1%
Isolatiesysteem	H
Nominale vermogensfactor	0.8
Gewicht dynamo (Kg)	492
Koellucht (m³/min)	37

OPEN TYPE GENERATOR AFMETINGEN (mm)

Lengte	2750
Breedte	1300
Hoogte	1751
Inhoud brandstoftank (lt.)	470

AFMETINGEN GENERATORKAST (mm)

Lengte	3934
Breedte	1356
Hoogte	2156
Droog gewicht (kg.)	2240
Inhoud brandstoftank (lt.)	470

1. Steel structures.
2. Emergency stop push button.
3. Control panel is mounted on the baseframe . Located at the right side of the generator set.



4. Corrosion-resistant locks and hinges.
5. Oil could be drained via valve and a hose
6. Exhaust system in the canopy.
7. Special large access doors for easy maintenance
8. In front and back side special large access doors for easy maintenance
9. Base frame -fuel tank.
10. Lifting points similar to ISO container , located on each top corner of the canopy.
11. The cap on the canopy provides easy access to radiator cap.
12. Sound proofing materials
13. Plastic air intake pockets.

Over Product

Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet even the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

Besturingskaart

Controle Module	DSE
Besturingsmodule model	DSE 6020
	1. Main status display. 2. Display scroll button. 3. Page(information) button. 4. Common alarm indicator. 5. Status LED's. 6. Operation selecting buttons.

Apparaten

- DSE, model 6020 Auto Mains Failure control module.
- Battery charger input 198-264 volt, output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
- Emergency stop push button and fuses for control circuits.

Structuur en verf

-Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

Montage

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator)

Generator regeleenheid

The DSE 6020 is a standard control module for our generator sets up to 200kVA and it has been designed to start and stop diesel and gas generator sets.

The DSE 6020 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.

Module monitors the mains supply and switch over to the generator when the mains power fails.

The DSE6020 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure. The LCD display indicates the fault.

Standaardfuncties

- Microprocessor controlled.



- LCD display makes information easy to read.
- 4-line, 64 x 132 pixel display.
- Automatically transfers between mains (utility) and generator power.
- Manual programming on front panel.
- User-friendly set-up and button layout.
- Remote start.
- Event logging (5) showing date and time.
- Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

Measurement indicators**ENGINE**

- Engine speed.
- Oil pressure.
- Coolant temperature.
- Run time.
- Battery volts.
- Configurable timing.

GENERATOR

- Voltage (L-L, L-N).
- Current (L1-L2-L3).
- Frequency.

MAINS

- Voltage (L-L, L-N).
- Frequency.
- Mains ready.
- Mains enabled.
- Gen. Set ready.
- Gen. Set enabled.

WARNING

- Charge failure.
- Battery Low/High voltage.
- Fail to stop.
- Low /High generator voltage.
- Under/over generator frequency.
- Over /Under speed.
- Low oil pressure.
- High coolant temperature.

SHUT DOWNS



- Fail to start. -Emergency stop.
- Low oil pressure.
- High coolant temperature.
- Over /Under speed.
- Under/over generator frequency.
- Under/over generator voltage.
- Oil pressure sensor open.
- Coolant temperature sensor open.

ELECTRICAL TRIP

- Generator over current.

Optie Kenmerken

- Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
- Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

Standaarden

- Electrical Safety / EMC compatibility
- BS EN 60950 Electrical business equipment.
- BS EN 61000-6-2 EMC immunity standard.
- BS EN 61000-6-4 EMC emission standard

Elektronische acculader

- Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC.

Proline 2405 has fully output short circuit protection and it can be used as a current source.

Proline 1205/2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.

Connect charge fail relay coil between positive output and CF output.

They are equipped with RFI filter to reduce electrical noise radiated from the device.

Galvanically isolated input and output typically 4kV for high reliability.

Standaardfuncties

- Water cooled, Diesel engine Radiator with mechanical fan Protective grille for rotating and hot parts Electric starter and charge alternator Starting battery (with lead acid) including rack and cables Engine coolant heater Base frame design incorporates an integral fuel tank and anti-vibration isolators Flexible fuel connection hoses Single bearing, class H alternator Industrial exhaust silencer and steel bellows supplied separately(for open sets) Static battery charger Manual for application and installation

Generator hardware-opties**TRANSFER SWITCH**

- Three or four pole motor operated circuit breaker

- Four Pole Contactor

- Three Pole Contactor



**OTHER ACCESSORIES**

- Supplied with oil and coolant - 30 °C
- Tool kit for maintenance
- Trailer
- Automatic transfer switch
- Main Fuel Tank
- Battery isolating switch
- Inlet and outlet acoustic baffles
- Low and high fuel level alarm
- Electrical oil drain pump
- Automatic or manual fuel filling system
- Duct adapter (on radiator)
- Enclosure: weater protective or sound attenuated
- Residential silencer

CONTROL SYSTEM

- Remote communication with modem
- Alarm output relays
- Charge Ammeter
- Earth fault, single set
- Remote relay output
- Paralel system with mains.
- Automatic synchronising and power control system (multi gen-set

Parallel)

- Remote annunciator panel
- Transition synchronization with mains

ENGINE

- Oil heater
- Low water level alarm
- Fuel-Water Seperator Filter

ALTERNATOR

- PMG excitation + AVR
- Main line circuit breaker
- Anti-Condensation Heater
- Over sized alternator

Certificaten

- TS ISO 8528
- CE
- SZUTEST
- 2000/14/EC

