



## FEATURES



### **FUEL GAUGE**

Fuel gauge is on the fuel tank



### **OHV**

Over Head Valve easy to maintenance



### **OIL LEVEL ALARM**

When the oil level is low that the engine will not start. voltage of a generator.



### **AVR**

AVR is a device often solid state, for controlling the output



### **MAINTENANCE FREE BATTERY**

It is long life



### **WHEEL KIT**

For easy transportation



### **CIRCUIT PROTECTOR**

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



### **LED DISPLAY**

LED screen to monitor voltage and current with hourmeter



### **GENERATOR SET OUT PUT SOCKETS**



### **CHOKE SYSTEM**

When the cold weather, choke system aid to operate the engine.



### **DUAL ELEMENT AIR FILTER**



### **LARGE CAPACITY FUEL TANK**

15-25lt

(Runtime may vary depending on fuel tank capacity)

## GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	6
Maximum Power (kW)	6,5
AC Rated Corrent (A)	26
DC Rated Corrent (A)	8
Voltage (V)	230
Frequency (Hz)	50
Phase Number	1
Power Factor	1
Fuel Consumption %100 (lt/h)	3,49
Fuel Consumption %75 (lt/h)	2,72
Fuel Consumption %50 (lt/h)	2,3
Run Time (h)	5
Noise Level (dB(A))	77
Sound Level (LwA)	97
Pole Number	2
Output Receptacle	2x16A/250v + 1x32A/200-250v

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)



444 4 630

| [www.aksa.com.tr](http://www.aksa.com.tr)



## ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	12,2
Engine Output (kW)	9,1
Bore and Stroke	90x66
Compression Ratio	8,8
Cylinder Number	1
Displacement (ml)	420
Fuel Type	Gasoline
Oil Capacity (L.)	1,1
Fuel Tank Capacity (L.)	31
Starting System	Electric/Manual
Cooling System	Air Cooled
Battery Capacity	14Ah

## DIMENSIONS AND WEIGHT

Width (mm.)	555
Lenght (mm.)	825
Height (mm.)	590
Dry Weight (kg.)	92,6