



FEATURES



FUEL GAUGE

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



AVR

AVR is a device often solid state, for controlling the output



MAINTENANCE FREE BATTERY

It is long life



WHEEL KIT

For easy transportation



CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



LED DISPLAY

LED screen to monitor voltage and current with hourmeter



GENERATOR SET OUT PUT SOCKETS



CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.



DUAL ELEMENT AIR FILTER



LARGE CAPACITY FUEL TANK

15-25lt

(Runtime may vary depending on fuel tank capacity)

GENERAL SPECIFICATIONS

3 Phase, 50 Hz, PF 0.8

AC Rated Power	kVA(kW)	6 (4,8)
Maximum Power	kVA(kW)	6,5 (5,2)
AC Nominal Current (A)		11
DC Rated Current (A)		8
Voltage (V)		230/400
Frequency (Hz)		50
Phase Number		3
Power Factor		0,8
Fuel Consumption %100 (lt/h)		3,49
Fuel Consumption %75 (lt/h)		2,72
Fuel Consumption %50 (lt/h)		2,3
Run Time (h)		5
Noise Level (dB(A))		77
Sound Level (LwA)		97
Pole Number		2
Output Receptacle		1x16A/415v

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)





ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	12,2
Engine Output (kW)	9,1
Bore and Stroke	90x66
Compression Ratio	8,8
Cylinder Number	1
Displacement (ml)	420
Fuel Type	Gasoline
Oil Capacity (L.)	1,1
Fuel Tank Capacity (L.)	31
Starting System	Electric/Manual
Cooling System	Air Cooled
Battery Capacity	14Ah

DIMENSIONS AND WEIGHT

Width (mm.)	555
Lenght (mm.)	825
Height (mm.)	590
Dry Weight (kg.)	93,5