



## FEATURES

### FUEL GAUGE

Fuel gauge is on the fuel tank

### OHV

Over Head Valve easy to maintenance

### OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.

### AVR

AVR is a device often solid state, for controlling the output

### CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.

### LED DISPLAY

LED screen to monitor voltage and current with hourmeter

### CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.

### DUAL ELEMENT AIR FILTER

### LARGE CAPACITY FUEL TANK

15-25lt

-Z μ v Ÿ u u Ç À Æ Ç % v ] v P } v ( μ o š v l % ] š Ç •

## GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	8
Maximum Power (kW)	8,8
AC Nominal Current (A)	3 4 ,8
Voltage (V)	
Frequency (Hz)	
Phase Number	
Power Factor	
Fuel Consumption %100 (lt/h)	7,3
Fuel Consumption %75 (lt/h)	5,9
Fuel Consumption %50 (lt/h)	4,33
Noise Level (dB(A))	82,6

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)



## ENGINE SPECIFICATIONS

Speed (Rpm)	36 00
Power (Hp)	18
Fuel Type	Gasoline
Oil Capacity (L.)	1,7
Fuel Tank Capacity (L.)	16
Starting System	Electric/Manual

## DIMENSIONS AND WEIGHT

Width (mm.)	740
Lenght (mm.)	910
Height (mm.)	750
Dry Weight (kg.)	122