



Over Product

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Kracht (kVA)

3 Fasen, 50 Hz, PF 0.8

Spanning	Stand-by vermogen (ESP)		Prime Power (PRP)		Standby Amper
	kW	kVA	kW	kVA	
400/231	592,00	740,00	540,00	675,00	1068,13

Stand-by vermogen (ESP) Het wordt gebruikt om te voldoen aan de variabele elektrische belastingvereiste in geval van uitval van de betrouwbare netvoeding. ESP voldoet aan ISO 8528-1 Overbelasting is niet toegestaan.

Prime Power (PRP) Wordt gedefinieerd als het continue bedrijfsvermogen onder variabele belasting. PRP voldoet aan ISO 8528-1 10% overbelasting kan elke 12 uur worden gedaan.

Algemene kenmerken

Modelnaam	AD 750
Frequentie (HZ)	50
Brandstoftype	Diesel
Motormerk en -model	HYUNDAI DP222LB
Alternatormerk en -model	AK 6540
Configuratiescherm Model	DSE 7320
Cabine	MS 85 TRP

MOTORSPECIFICATIES

Motor	HYUNDAI
Motor model	DP222LB
Silindir Sayısı (L)	12 cylinders - V type
Bore (mm.)	128
Stroke (mm.)	142
Silindir Hacmi (lt.)	21.927
Aspiratie	Turbo Charged and Intercooled (Air to Air)
Compressieverhouding	15.0:1
Hız (d/dk)	1500
Olie capaciteit (Filtre Dahil) (lt)	40
Stand-by vermogen (kW/HP)	664/903
Prime Power (kW/HP)	604/821
Blokverwarmingshoeveelheid	1
Blokkeer verwarmingsvermogen (Watt)	3000
Brandstoftype	Diesel
Injectietype en systeem	Direct
Type brandstofpomp	WEIFU in-line "P" type
Governor-systeem	Electronic
Bedrijfsspanning (Vdc)	24 Vdc

De fabrikant behoudt zich het recht voor om zonder voorafgaande kennisgeving wijzigingen aan te brengen in het model, technische specificaties, kleur, uitrusting, accessoires en afbeeldingen. (25.12.2023)





Batterij en capaciteit (aantal / Ah)	2x143
Laaddynamo (A)	45
Koelmethode	Water Cooled
Koelventilatorluchtstroom (m ³ / min)	860
Koelvloeistofcapaciteit (alleen motor / met radiator) (lt)	23/104.2
Luchtfilter	Dry Type
Brandstofverbruik bij eerste 100% belasting (lt / uur)	147.1
Brandstofverbruik primair 75% belasting (lt / uur)	109.2
Brandstofverbruik bij eerste 50% belasting (lt / uur)	73

Dynamo specificaties

Fabrikant	Aksa
Alternatormerk en -model	AK 6540
Frequentie (HZ)	50
Kracht (kVA)	675
Spanning (V)	400
Fase	3
Automatische spanningsregelaar	SX440
Voltage regulatie	(+/-)1%%
Isolatiesysteem	H
Bescherming	IP22
Nominale vermogensfactor	0.8
Gewicht dynamo (Kg)	1685
Koellucht (m ³ /min)	62.1

OPEN TYPE GENERATOR AFMETINGEN (mm)

Lengte	3470
Breedte	1550
Hoogte	2262
Droog gewicht (kg.)	4190
Inhoud brandstoftank (lt.)	1000

AFMETINGEN GENERATORKAST (mm)

Lengte	5282
Breedte	1605
Hoogte	2504
Droog gewicht (kg.)	5400
Inhoud brandstoftank (lt.)	1000

1. Steel structures.
2. Emergency stop push button.
3. Control panel is mounted on the baseframe . Located at the right side of the generator set.





4. Corrosion-resistant locks and hinges.
5. Oil could be drained via valve and a hose
6. Exhaust system in the canopy.
7. Special large access doors for easy maintenance
8. In front and back side special large access doors for easy maintenance
9. Base frame -fuel tank.
10. Lifting points similar to ISO container , located on each top corner of the canopy.
11. The cap on the canopy provides easy access to radiator cap.
12. Sound proofing materials
13. Plastic air intake pockets.

Over Product

Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet even the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

Besturingskaart

Controle Module	DSE
Besturingsmodule model	DSE 7320
İletişim Portları	MODBUS
	1. Menu navigation buttons 2. Close mains button 3. Main Status and instrumentation display 4. Alarm LED's 5. Close generator button 6. Status LED's 7. Operation selecting buttons

Apparaten

DSE, model 7320 Auto Mains Failure control module Static battery charger Emergency stop push button and fuses for control circuits

Structuur en verf

Components installed in sheet steel enclosure.

Phosphate chemical, pre-coating of steel provides corrosion resistant surface

Polyester composite powder topcoat forms high gloss and extremely durable finish

Lockable hinged panel door provides for easy component access

Montage

Control panel is mounted generating set baseframe on robust steel stand or power module. Located at side of generating set with properly panel visibility.

Generator regeleenheid

The DSE 7320 control module is a standard addition to our generator sets from 220 kVA upwards and it has been designed to start and stop diesel and gas generating sets that include electronic and non electronic engines.

The DSE 7320 includes the additional capability of being able to monitor a mains (utility) supply and is therefore suitable for controlling a standby generating set in conjunction with an automatic transfer switch.

The DSE7320 also indicates operational status and fault conditions, automatically shutting down the generating set and indicating faults by means of its LCD display on the front panel.

Standaardfuncties

Microprocessor controlled





- 132 x 64 pixel LCD display makes information easy to read
- Front panel programming and also via PC software
- Soft touch membrane keypad and five key menu navigation
- Remote communications via RS232, RS485 and ethernet.
- Event logging (50) showing date and time
- Multiple date and time engine exercise mode and maintenance scheduler
- Engine block heater control.
- Controls; stop, manuel, auto, test, start, mute lamb test/transfer to generator, transfer to mains, menu navigation.

Meetindicatoren**ENGINE**

Engine speed
Oil pressure
Coolant temperature
Run time Battery volts
Engine maintenance due

GENERATOR

Voltage (L-L, L-N)
Current (L1-L2-L3)
Frequency
Earth current

kW
Pf
kVA_r
kWh, kVA_h, kVA_r_h

Phase sequence

MAINS

Voltage (L-L, L-N)
Frequency

WARNING

Charge failure
Battery under voltage
Fail to stop
Low fuel level (opt.)
kW over load
Negative phase sequence
Loss of speed signal

PRE-ALARMS



Low oil pressure
High engine temperature
Low engine temperature
Over /Under speed
Under/over generator frequency
Under/over generator voltage
ECU warning
SHUT DOWNS
Fail to start
Emergency stop
Low oil pressure
High engine temperature
Low coolant level
Over /Under speed
Under/over generator frequency
Under/over generator voltage
Oil pressure sensor open
Phase rotation
ELECTRICAL TRIP
Earth fault
kW over load
Generator over current
Negative phase sequence

Optie Kenmerken

High oil temperature shut down
Low fuel level shut down
Low fuel level alarm
High fuel level alarm
EXPANSION MODULES
Editional LED module (2548)
Expansion relay module (2157)
Expansion input module (2130)

Standaarden

Electrical Safety / EMC compatibility
BS EN 60950 Electrical business equipment
BS EN 61000-6-2 EMC immunity standard
BS EN 61000-6-4 EMC emission standard

Elektronische acculader



Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

Battery charger models' output V-I characteristic is very close to square

2405 has fully output short circuit protection and it can be used as a current source.

2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.

Charge fail output is available.

Connect charge fail relay coil between positive output and CF output.

Input: 196-264V.

Output: 27,6V 5A or 13,8V 5A.

Standardfuncties

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately(for open sets)
- Static battery charger
- Manual for application and installation

Generator hardware-opties

ENGINE

Fuel-Water Separator Filter

Oil heater

ALTERNATOR

Anti-Condensation Heater

Over sized alternator

PMG excitation + AVR

Main line circuit breaker

CONTROL SYSTEM

Automatic synchronising and power control system (multi gen-set Parallel)

Transition synchronization with mains

Remote annunciator panel

Remote relay output

Alarm output relays

Remote communication with modem





Earth fault, single set

Charge Ammeter

TRANSFER SWITCH

Three Pole Contactor

Four Pole Contactor

Three or four pole motor operated circuit breaker

OTHER ACCESSORIES

Main Fuel Tank

Automatic or manual fuel filling system

Manual oil drain pump

Electrical oil drain pump

Low and high fuel level alarm

Residential silencer

Enclosure: weater protective or sound attenuated

Duct adapter (on radiator)

Inlet and outlet motorised louvers

Inlet and outlet acoustic baffles

Trailer

Tool kit for maintenance

Automatic transfer switch

Certificaten

- ISO 14001-2004
- TS ISO 8528
- TS ISO 9001-2008
- CE
- SZUTEST
- 2000/14/EC

