



Over Product

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Kracht (kVA)

3 Fasen, 60 Hz, PF 0.8

Spanning	Stand-by vermogen (ESP)		Prime Power (PRP)		Standby Amper
	kW	kVA	kW	kVA	
380/220	177,60	222,00	160,00	200,00	337,30
208/120	200,00	250,00	183,20	229,00	693,95
480/277	200,00	250,00	183,20	229,00	693,95

Stand-by vermogen (ESP) Het wordt gebruikt om te voldoen aan de variabele elektrische belastingvereiste in geval van uitval van de betrouwbare netvoeding. ESP voldoet aan ISO 8528-1 Overbelasting is niet toegestaan.

Prime Power (PRP) Wordt gedefinieerd als het continue bedrijfsvermogen onder variabele belasting. PRP voldoet aan ISO 8528-1 10% overbelasting kan elke 12 uur worden gedaan.

Algemene kenmerken

Modelnaam	AD 250-6
Frequentie (HZ)	60
Brandstoftype	Diesel
Motormerk en -model	HYUNDAI P086 TI - 60Hz
Alternatormerk en -model	ECO 38-2S/4 A - 60Hz
Configuratiescherm Model	DSE 7320
Cabine	AK 50

MOTORSPECIFICATIES

Motor	HYUNDAI
Motor model	P086 TI - 60Hz
Silindir Sayısı (L)	6 cylinders - in line
Bore (mm.)	111
Stroke (mm.)	139
Silindir Hacmi (lt.)	8.071
Aspiratie	Turbo Charged and Intercooled (Air to Air)
Compressieverhouding	16.4:1
Hız (d/dk)	1800
Olie capaciteit (Filtre Dahil) (lt)	15.5
Stand-by vermogen (kW/HP)	223/299
Blokverwarmingshoeveelheid	1
Blokkeer verwarmingsvermogen (Watt)	1500
Brandstoftype	Diesel
Injectietype en systeem	Direct
Type brandstofpomp	Zexel P inline





Governor-systeem	Electronic
Bedrijfsspanning (Vdc)	24 Vdc
Batterij en capaciteit (aantal / Ah)	2x85
Laaddynamo (A)	45
Koelmethode	Water Cooled
Koelventilatorluchtstroom (m ³ / min)	250
Koelvloeistofcapaciteit (alleen motor / met radiator) (lt)	14/46
Luchtfilter	Dry Type
Brandstofverbruik bij eerste 100% belasting (lt / uur)	50.6
Brandstofverbruik primair 75% belasting (lt / uur)	37.7
Brandstofverbruik bij eerste 50% belasting (lt / uur)	25.1

Dynamo specificaties

Fabrikant	Mecc Alte
Alternatormerk en -model	ECO 38-2S/4 A - 60Hz
Frequentie (HZ)	60
Kracht (kVA)	164
Spanning (V)	380
Fase	3
Automatische spanningsregelaar	DSR
Voltage regulatie	(+/-)1%
Isolatiesysteem	H
Bescherming	IP23
Nominale vermogensfactor	0.8
Gewicht dynamo (Kg)	560
Koellucht (m ³ /min)	39

OPEN TYPE GENERATOR AFMETINGEN (mm)

Lengte	2688
Breedte	1150
Hoogte	1624
Droog gewicht (kg.)	1800
Inhoud brandstoftank (lt.)	380

AFMETINGEN GENERATORCAST (mm)

Lengte	3404
Breedte	1206
Hoogte	2020
Droog gewicht (kg.)	2175
Inhoud brandstoftank (lt.)	380

1. Steel structures
2. Emergency stop push button
3. Control panel is right side of the set.



4. Corrosion resistant locks and hinges
5. Sump drains valves
6. Sound proof foam material
7. Lifting Points

Over Product

Sound-attenuated and Weather-protective Enclosures Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet even the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

Besturingskaart

Controle Module	DSE
Besturingsmodule model	DSE 7320
İletişim Portları	MODBUS
	1. Menu navigation buttons 2. Close mains button 3. Main Status and instrumentation display 4. Alarm LED's 5. Close generator button 6. Status LED's 7. Operation selecting buttons

Apparaten

DSE, model 7320 Auto Mains Failure control module Static battery charger Emergency stop push button and fuses for control circuits

Structuur en verf

Components installed in sheet steel enclosure.

Phosphate chemical, pre-coating of steel provides corrosion resistant surface

Polyester composite powder topcoat forms high gloss and extremely durable finish

Lockable hinged panel door provides for easy component access

Montage

Control panel is mounted generating set baseframe on robust steel stand or power module. Located at side of generating set with properly panel visibility.

Generator regeleenheid

The DSE 7320 control module is a standard addition to our generator sets from 220 kVA upwards and it has been designed to start and stop diesel and gas generating sets that include electronic and non electronic engines.

The DSE 7320 includes the additional capability of being able to monitor a mains (utility) supply and is therefore suitable for controlling a standby generating set in conjunction with an automatic transfer switch.

The DSE7320 also indicates operational status and fault conditions, automatically shutting down the generating set and indicating faults by means of its LCD display on the front panel.

Standaardfuncties

Microprocessor controlled

- 132 x 64 pixel LCD display makes information easy to read
- Front panel programming and also via PC software
- Soft touch membrane keypad and five key menu navigation
- Remote communications via RS232, RS485 and ethernet.
- Event logging (50) showing date and time



- Multiple date and time engine exercise mode and maintenance scheduler
- Engine block heater control.
- Controls; stop, manuel, auto, test, start, mute lamb test/transfer to generator, transfer to mains, menu navigation.

Meetindicatoren**ENGINE**

Engine speed
Oil pressure
Coolant temperature
Run time Battery volts
Engine maintenance due

GENERATOR

Voltage (L-L, L-N)
Current (L1-L2-L3)
Frequency
Earth current
kW
Pf
kVAr

kWh, kVAh, kVArh
Phase sequence

MAINS

Voltage (L-L, L-N)
Frequency

WARNING

Charge failure
Battery under voltage
Fail to stop
Low fuel level (opt.)
kW over load
Negative phase sequence
Loss of speed signal

PRE-ALARMS

Low oil pressure
High engine temperature
Low engine temperature
Over /Under speed
Under/over generator frequency
Under/over generator voltage





ECU warning
SHUT DOWNS
Fail to start
Emergency stop
Low oil pressure
High engine temperature
Low coolant level
Over /Under speed
Under/over generator frequency
Under/over generator voltage
Oil pressure sensor open
Phase rotation
ELECTRICAL TRIP
Earth fault
kW over load
Generator over current
Negative phase sequence

Optie Kenmerken

High oil temperature shut down
Low fuel level shut down
Low fuel level alarm
High fuel level alarm
EXPANSION MODULES
Editional LED module (2548)
Expansion relay module (2157)
Expansion input module (2130)

Standaarden

Electrical Safety / EMC compatibility
BS EN 60950 Electrical business equipment
BS EN 61000-6-2 EMC immunity standard
BS EN 61000-6-4 EMC emission standard

Elektronische acculader

Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

Battery charger models' output V-I characteristic is very close to square

2405 has fully output short circuit protection and it can be used as a current source.

2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.



Charge fail output is available.

Connect charge fail relay coil between positive output and CF output.

Input: 196-264V.

Output: 27,6V 5A or 13,8V 5A.

Standaardfuncties

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately (for open sets)
- Static battery charger
- Manual for application and installation

Generator hardware-opties

TRANSFER SWITCH

- Motor Switch
- Four Pole Contactor
- Three Pole Contactor

OTHER ACCESSORIES

- Tool kit for maintenance
- Trailer
- Inlet and outlet acoustic baffles
- Double wall chassis
- Automatic transfer switch
- Main Fuel Tank
- Supplied with oil and coolant - 30 °C
- Inlet and outlet motorised louvers
- Electrical oil drain pump
- Manual oil drain pump
- Automatic or manual fuel filling system
- Low and high fuel level alarm
- Duct adapter (on radiator)
- Enclosure: weater protective or sound attenuated
- Residential silencer

CONTROL SYSTEM





- Remote communication with modem
- Alarm output relays
- Charge Ammeter
- Earth fault, single set
- Transition synchronization with mains
- Automatic synchronising and power control system (multi gen-set Parallel)
- Remote relay output
- Remote annunciator panel

ENGINE

- Oil heater
- Fuel-Water Separator Filter

ALTERNATOR

- PMG excitation + AVR
- Main line circuit breaker
- Anti-Condensation Heater
- Over sized alternator

Certificaten

- TS ISO 8528
- CE
- SZUTEST
- 2000/14/EC